

Upload config file to InfiLINK XG / InfiLINK XG 1000



Successfully pass the free certification exam at IW Academy and become an Infinet Certified Engineer.

[To the certification exam](#)

Introduction

This document contains the requirements for uploading the configuration file to the InfiLINK XG / InfiLINK XG 1000 devices. In order for the configuration file downloaded from one device to be correctly downloaded and applied with all the settings on the other, you need to follow the procedure below.

Procedure

- Download required configuration file.
- Exclude everything in the downloaded configuration file that starts from "xg -v3-start" and ends with "xg -v3-end".

Example: Text for exclusion

```
xg -v3-start
xg -v3 41b0ff1c56c4110f448bb8b934549b2d .BwNwSRCE9FYJPTxafSo1MuyELPNqTPOoX00o26s
xg -v3 hvpoem+LvpqFMYKzEiKSDYbmIfKFx1wsJCmkLj3soNqq/9y9meHnHwf1ZWyT33fkKm5U/4fI
xg -v3 VMLJqlyUznEPQzf8x8Rhrg4BMJWgg3IzED5cr1Q0H33iJTVFK2byuHjfNqXjv22i6qzmrxGM
xg -v3 kRH6hEXzpNLHzYf5I665H/crcHvGUPRU6dVoc+JXTzqF/R7ngHhMkakAbvLtnPYaJkc+u64v
xg -v3 DCe61X62U5m/3CGr1bK7s6bnfx775/9CidbnDLuVPT5NyIwLrMqWnBN8DiLR2jVmMxi3DtI1
xg -v3 5YIDkJuBzfqNHyophMi9P/Ojj13tj831CuTetSZQoqAKu2kq8XItJQ4U+KHtyeJBQV0XdxO
xg -v3 J13aVMrJIA13MTpxwIKmch8idL7su0pvsDsUkPJFkrZkUhB8NjceZzV4Hvt9jdwpvpv7Qk1
xg -v3 JdoEz4xQ/Gr2aANOVhN+mLU2p0Wj7cmZ8OhzZFD3CKLHgA5YkLJmZNz0ZYxsZBFlyIqLUbG
xg -v3 jHsXNjvCadtNpxFbIAxu85hEnUYn1nLdCBwLOYPimSB2SMTBnFDhxeXrZn1Ug1s5/ILVCpeR
xg -v3 Boxq5xV2soIwgK1tFBMF+aIIuajtH7c5N24bAl1c6YkGbV6y4ulu5PMIUDiyOCtye7wXFco
xg -v3 u0u7gfq9C3VQs55QkkA9pL61Zmmn9ivc6k+ZszLoi1W78JDSyZnAmN6DVuT/c64vSM2cXCKt
xg -v3 54H0eqaM7bOzQGsiR1da0SrIFnxqohP11LoOU9YX8HUVfgo8h1H2Izv1Zx14n0Lto36x3Yx
xg -v3 1rRlKHNAvKnj+15Sw0KRS26Y//ACqakAbXCL4mB1OV69nFRuYkqEJDgiN5wF8gnXKtqcoK
xg -v3 FBn1/tM5QkPtlrYz73zaZJrYW14BwX5gBbRZ9/iEXJzMddzMi/HWzvPtcfJ128Su/QyGEyE0
xg -v3 Fc4Qx182rXByNd/tUdBG1lHKUE8JT4308rtD3zkPFNaM+CZhVWLHZ4FqdfcLmX6s5TsiT2b4
xg -v3 Za3zItpKSe6B1rN7nhTCngLrw/oIrue4nfkZqEoVOh9w2oMi9MIZkcfP95Ev3X48Afqljx5D
xg -v3 YuZ2XeamGBGGj14EG4HqdCRMWFG61cDknzMxkgftxk35sLAX5NDjBc9asmRvEskiqDBqNO6
xg -v3 H9ZZAbe4mQU5h6QA8rVxfVHgGJ40yylfTltsOvCzGpJWWI9q/c6cgZiyuY63rs47kArhFtrf
xg -v3 PT+eb2d9iEqpoZJBuemIxIcRR9M+2BEyhC7/zy8UYdqYkcNUbHqokVgl0VB0oTzzdNiDw0sx
xg -v3 wVz4qEzGZ3Xn/c4AmXF24NyS5w5f8A9Np
xg -v3-end
```

- Delete the "#" signs above the "xg -v3-start" section everywhere where settings are and save changes.

Example: Config part with # sign deleted

```
#Link shared settings (Radio Front End):
xg -cell-id 0
xg -channel-width 20
xg -freq-dl 4980
xg -freq-ul 4980
xg -short-cp 1
xg -freq-auto 0
```

- Upload updated configuration file to the device.