

## Apply, Try and Preview buttons for the configuration



Successfully pass the free certification exam at IW Academy and become an Infinet Certified Engineer.

[To the certification exam](#)

After performing the needed configuration in the "Basic Settings" menu, you must save all the new parameters by clicking the «**Apply**» button. If you are not sure about the effect of the new configuration performed, you can apply the new configuration temporarily by clicking the «**Test**» button. The previous configuration is automatically restored after a grace period of 180 seconds (3 minutes). You have the options to extend the grace period, or immediately accept/reject the changes.

By clicking the «**Preview Configuration**» button, you can view the configuration results in CLI format. In order to display all changes added to configuration in CLI format since last save, click the «**Show changes**» button.

A warning message is displayed in this section to inform about the consequences of saving configuration via Web or CLI interfaces:

### Warning!

After pressing "Apply" button all the settings made via command-line interface from the sections present in this configuration page will be replaced. After pressing "Test" button the new configuration will be temporarily activated for about 3 minutes.

### Figure - Apply, test and preview the configuration

After clicking the «**Apply**» button for saving the new configuration, the system will redirect you to the login page. After a 5 seconds timer you can log in back to the unit and check the new configuration.